



Model Number X1805 Bandpass Filter

Rev.-
01/02/07

Features:

- Cavity Design
- Low Loss

Applications:

- Radar
- Test Equipment

Package size:

- 0.75 x 1.5 x 4.0"

(Please see outline for exact dimensions)



Specifications: (+25C)

Passband	9500 to 10000 MHz
Insertion Loss	1.0 dB
VSWR	1.5:1
Rejection	10 dB @ 9400 MHz
Rejection	10 dB @ 10100 MHz
Connectors	SMA Female / SMA Male

Delta Microwave

1301 Vanguard Dr.
Oxnard, CA. 93033

Phone: 805.240.1044
Fax: 805.240.9544

email: sales@deltamicrowave.com
www.deltamicrowave.com

--	--

By

Checked